

  
**ICOM**

VHF TRANSCEIVER

# IC-V8

General (LM) version

Rugged  
MIL-STD 810

## Professional quality and functions

- Simple operation and tough construction
- 54×132×35 mm compact body
- Powerful 5.5W of output power
- 100 memory channels plus 1 call channel
- 5 character alphanumeric display
- Priority, program, memory, skip and tone scanning
- Built-in CTCSS and DTCSS encoder/decoder
- Built-in DTMF encoder
- Indicated "Function + Short-cut" menus
- Ni-MH or Ni-Cd battery pack available
- Optional DTMF decoder unit, UT-108 with ANI
- Optional voice scrambling unit, UT-109 or UT-110



Icom Inc.

## SPECIFICATIONS

### GENERAL

- Frequency coverage : 136-174MHz\*  
\*Guaranteed range 144-148MHz
- Mode : FM (F3E, F2D)
- No. of memory Ch. : 107 (incl. 6 scan edges and 1 call)
- Frequency stability : ±10ppm (-10°C to +60°C)
- Operating temperature range:  
-10°C to +60°C; +14°F to +140°F
- Power supply requirement : 7.2V DC (6.0-10.3V DC acceptable; Icom's battery pack only)
- Current drain (at 7.2V DC):

Tx	5.5W	2.0A
	0.5W	0.8A
Rx	Max. audio	250mA
	Standby	70mA
	Power saved	20mA

- Antenna connector : BNC (50Ω)
- Dimensions : 54(W)×132(H)×35(D) mm; (proj. not incl.)
- Weight (approx.) : 350g; 12.3oz (w/ant. and BP-222N)

### TRANSMITTER

- Output power : High 5.5W (at 7.2V DC) Low 0.5W
- Spurious emissions : Less than -60dB
- Max. freq. deviation : ±5.0kHz
- Ext. mic. connector : 3-conductor 2.5(d)mm (1/10") /2.2kΩ

### RECEIVER

- Receiving system : Double conversion super-heterodyne
- Intermediate freq. : 1st 21.7MHz  
2nd 450kHz
- Sensitivity : 0.16μV (typ.; at 12dB SINAD)
- Squelch sensitivity : 0.10μV (typ.; threshold)
- Selectivity : 65dB (typical)
- Intermodulation : 75dB (typical)
- Spurious and image rejection: 75dB (typical)

- Audio output power : 300mW with an 8Ω load (at 7.2V DC)
- Ext. SP connector : 3-conductor 3.5(d)mm (1/8") /8 Ω

### Supplied accessories

- Battery case or battery pack\* ● Desktop charger\*
- Antenna ● Belt clip \*depending on version

### Applicable U.S. Military Specifications

Standard	MIL 810 C		MIL 810 D		MIL 810 E		MIL 810 F	
	Method	Proc.	Method	Proc.	Method	Proc.	Method	Proc.
Low Pressure	500.1	I	500.2	I, II	500.3	I, II	500.4	I, II
High Temp.	501.1	I	501.2	I, II	501.3	I, II	501.4	I, II
Low Temp.	502.1	I	502.2	I, II	502.3	I, II	502.4-3	I, II
Temp. Shock	503.1	I	503.2	I, II	503.3	I	503.4	I
Solar Radiation	505.1	I	505.2	I	505.3	I	505.4	I
Rain	506.1	I, II	506.2	I, II	506.3	I, II	506.4	I, II
Humidity	507.1	I, II	507.2	II, III	507.3	II, III	507.4	-
Salt Fog	509.1	I	509.2	I	509.3	I	509.4	-
Dust	510.1	I	510.2	I	510.3	I	510.4	I
Vibration	514.2	VIII, X	514.3	I	514.4	I	514.5	I
Shock	516.2	I, II, V	516.3	I, IV	516.4	I, IV	516.5	I, IV

All stated specifications are subject to change without notice or obligation.

## OPTIONS

### BATTERY PACKS AND CASE

- BP-208N** AA (LR6) batteries × 6
- BP-209N** Ni-Cd 7.2V/1100mAh
- BP-210N** Ni-MH 7.2V/1650mAh
- BP-222N** Ni-Cd 7.2V/600mAh



BATTERY PACKS AND CASE	BP-208N	BP-209N	BP-210N	BP-222N
OUTPUT POWER	5.5W typ.*	5.5W typ.	5.5W typ.	5.5W typ.
BATTERY LIFE	-	7.5hours	11hours	4.0hours

Approx. battery life; Tx (Hi); Rx: standby=5:5:90 with auto power save  
\* The LOW output power selection is recommended.

### REGULAR CHARGER



**BC-146** DESKTOP CHARGER + **BC-147A/E** AC ADAPTER  
Charges a battery pack, BP-209N, BP-210N or BP-222N with/without transceiver in 12, 18.5, 6.5 hours (approx.), respectively. BC-137 is also available for regular charging.

### RAPID CHARGER



**BC-144N** DESKTOP CHARGER + **BC-145A/E/V** AC ADAPTER  
For rapid charging of battery pack, BP-209N, BP-210N or BP-222N. An AC adapter, BC-145, is supplied with the charger depending on version. Charging time: 1.5 to 2 hours. BC-119N is also available for rapid charging.  
**BC-121N** MULTI-CHARGER + **AD-94** (Ver. 11) DESKTOP CHARGER ADAPTER + **BC-157** AC ADAPTER  
For rapid charging of up to 6 battery packs (Six AD-94s are required), BP-209N, BP-210N or BP-222N. An AC adapter, BC-157, may be supplied, depending on version. Charging time: 1.5 to 2 hours.

### SPEAKER-MICROPHONES



- HM-46L**: Slim dimensions. Equipped with an earphone jack and a transmit indicator.
- HM-75A**: Allows you to remotely select operating channel, etc., according to program.
- HM-158L**: Compact and durable body with screw-type connector. Equipped with an earphone jack and a revolving clip.
- HM-159L**: Full size durable microphone with revolving clip.
- HM-153L**: Durable earphone-microphone with revolving clip.

### INTERNAL UNITS



- UT-108** DTMF DECODER  
Provides DTMF decode and ANI capabilities.
- UT-109/UT-110** VOICE SCRAMBLER UNITS  
Provides operating security.  
UT-109: Non rolling type.  
UT-110: Rolling type.

- CS-V8** CLONING SOFTWARE + **OPC-478** CLONING CABLE  
Provides quick and easy programming of memory channel, memory names, etc.
- MB-86/MB-103** BELT CLIPS  
MB-103: Alligator type clip. Same as supplied.  
MB-86: Swivel belt clip.
- MB-96N/MB-96F** LEATHER BELT HANGERS  
MB-96N: Swivel belt hanger.  
MB-96F: Fixed type belt hanger. Use with MB-103.
- OPC-474** CLONING CABLE  
Used for transceiver-to-transceiver data cloning.
- OPC-656** DC POWER CABLE  
For use the BC-121N with a DC power supply.
- SP-13** EARPHONE  
Provides clear audio even in noisy environments.
- HS-51** HEADSET  
For hands-free operation. Includes VOX, PTT and "one-touch" PTT with a time-out timer.

Icom Inc. 1-1-32, Kami-minami, Hirano-ku, Osaka 547-0003, Japan Phone: +81 (06) 6793 5302 Fax: +81 (06) 6793 0013

URL: <http://www.icom.co.jp/world/index.html>

Count on us!

### Icom America Inc.

2380 116th Avenue NE,  
Bellevue, WA 98004, U.S.A.  
Phone : +1 (425) 454-8155  
Fax : +1 (425) 454-1509  
E-mail : sales@icomamerica.com  
URL : <http://www.icomamerica.com>

### Icom New Zealand

146A Harris Road, East Tamaki,  
Auckland, New Zealand  
Phone : +64 (09) 274 4062  
Fax : +64 (09) 274 4708  
E-mail : inquiries@icom.co.nz  
URL : <http://www.icom.co.nz>

### Icom (UK) Ltd.

Unit 9, Sea St., Herne Bay,  
Kent, CT6 8LD, U.K.  
Phone : +44 (0)1227 741741  
Fax : +44 (0)1227 741742  
E-mail : info@icomuk.co.uk  
URL : <http://www.icomuk.co.uk>

### Asia Icom Inc.

6F No. 68, Sec. 1 Cheng-Teh Road,  
Taipei, Taiwan, R.O.C.  
Phone : +886 (02) 2559 1899  
Fax : +886 (02) 2559 1874  
E-mail : sales@asia-icom.com  
URL : <http://www.asia-icom.com>

Your local distributor/dealer:

### Icom Canada

Glenwood Centre #150-6165 Highway 17,  
Delta, B.C., V4K 5B8, Canada  
Phone : +1 (604) 952-4266  
Fax : +1 (604) 952-0090  
E-mail : info@icomcanada.com  
URL : <http://www.icomcanada.com>

### Icom (Europe) GmbH

Communication Equipment  
Himmelgeister Str. 100,  
D-40225 Düsseldorf, Germany  
Phone : +49 (0211) 346047  
Fax : +49 (0211) 333639  
E-mail : info@icom-europe.com  
URL : <http://www.icomeurope.com>

### Icom France s.a.s.

Zac de la Plaine,  
1 Rue Brindejone des Moulinais, BP 45804,  
31505 Toulouse Cedex 5, France  
Phone : +33 (5) 61 36 03 03  
Fax : +33 (5) 61 36 03 00  
E-mail : icom@icom-france.com  
URL : <http://www.icom-france.com>

### Beijing Icom Ltd.

10C07, Long Silver Mansion, No.88, Yong Ding  
Road, Haidian District, Beijing, 100039, China  
Phone : +86 (010) 5889 5391/5392/5393  
Fax : +86 (010) 5889 5395  
E-mail : bjicom@bjicom.com  
URL : <http://www.bjicom.com>

### Icom (Australia) Pty. Ltd.

Unit 1 / 103 Garden Road,  
Clayton, VIC 3168 Australia  
Phone : +61 (03) 9549 7500  
Fax : +61 (03) 9549 7505  
E-mail : sales@icom.net.au  
URL : <http://www.icom.net.au>

### Icom Spain S.L.

Ctra. Rubi, No. 88 "Edificio Can Castanyer"  
08190, Sant Cugat del Valles, Barcelona, Spain  
Phone : +34 (93) 590 26 70  
Fax : +34 (93) 589 04 46  
E-mail : icom@icomspain.com  
URL : <http://www.icomspain.com>

### Icom Polska

Sopot, 3 maja 54, Poland  
Phone : +48 (58) 550 7135  
Fax : +48 (58) 551 0484  
E-mail : icompolska@icompolska.com.pl  
URL : <http://www.icompolska.com.pl>